

Data Sheet

RoamAlert® Securaband™ Tag

The RoamAlert Securaband Tag provides protection for wander-prone residents. Each tag is identified by its own unique code. The system generate an Exit alarm if the tag is brought near an exit protected by a Door Controller. The Securaband Tag can be worn on the individual’s wrist or ankle and is attached using the RoamAlert Securaband strap. When attached, the tag provides additional tamper-resistant protection for residents.



Securaband Tag Specifications	
Part Number	804A2401
Model	SecuraBand Tag
Output Frequency	433.92 MHz
Input Frequency	307 kHz
Battery Life	Three years
Temperature	14° to 122°F (-10° to 50°C)
Humidity	0-95% RH @ 70°F (21°C), non-condensing
Dimensions	Approx. 1.08 x 1.16 x 0.6” (2.74 x 2.95 x 1.5 cm)
Weight	Approximately 0.26 oz. (7.5 g)

Product Highlights

- Unique electronic serial number to identify each tag
- High capacity battery (3 years)
- Smooth surface permits easy sterilization and prevents harboring of bacteria
- Attractive, high-impact, tamper-resistant case
- Waterproof
- Small and unobtrusive



Phone: 800-824-2996
 North America: stanleyhealthcare@sbdinc.com
 Latin America: stanleyhealthcare-latam@sbdinc.com

Middle East: stanleyhealthcare-MEA@sbdinc.com
 Asia Pacific: stanleyhealthcare-asiapac@sbdinc.com
 Europe: shs-uk@sbdinc.com